

FRS/GMRS Channel	Freq (MHz)	GMRS Power	GMRS Bandwidth	FRS/GMRS Channel	Freq (MHz)	GMRS Power	GMRS Bandwidth
1	462.5625	5 W	20 kHz	12	467.6625	0.5 W	12.5 kHz
2	462.5875	5 W	20 kHz	13	467.6875	0.5 W	12.5 kHz
3	462.6125	5 W	20 kHz	14	467.7125	0.5 W	12.5 kHz
4	462.6375	5 W	20 kHz	15	462.5500	50 W	20 kHz
5	462.6625	5 W	20 kHz	16	462.5750	50 W	20 kHz
6	462.6875	5 W	20 kHz	17	462.6000	50 W	20 kHz
7	462.7125	5 W	20 kHz	18	462.6250	50 W	20 kHz
8	467.5625	0.5 W	12.5 kHz	19	462.6500	50 W	20 kHz
9	467.5875	0.5 W	12.5 kHz	20	462.6750	50 W	20 kHz
10	467.6125	0.5 W	12.5 kHz	21	462.7000	50 W	20 kHz
11	467.6375	0.5 W	12.5 kHz	22	462.7250	50 W	20 kHz

PL Tone / CTCSS / CTCS / Privacy Code

1	67
2	71.9
3	74.4
4	77
5	79.7
6	82.5
7	85.4
8	88.5
9	91.5
10	94.8
11	97.4
12	100
13	103.5

14	107.2
15	110.9
16	114.8
17	118.8
18	123
19	127.3
20	131.8
21	136.5
22	141.3
23	146.2
24	151.4
25	156.7
26	162.2

27	167.9
28	173.8
29	179.9
30	186.2
31	192.8
32	203.5
33	210.7
34	218.1
35	225.7
36	233.7
37	241.8
38	250.3

REVISED: 2020-05-29